

UMD 707RCM - Measuring equipment for the top hat rail

Download data sheet



UMD 707RCM

The UMD 707RCM is a compact, high-end residual current measurement device for installation on the DIN top hat rail. It measures 5-channel residual currents (type A) and the voltage quality (harmonics up to the 128th harmonic; voltage dips 40 µsec).

Measurement is performed via the RCM-CT residual current transformer.

The device has a large 512 MB memory. The device can be accessed via the Ethernet interface and live measured values can be observed using the web browser via the corresponding web server. Therefore, internet protocols such as NTP can also be read in.

PLC systems and building management systems can be connected easily via modbus TCP. Digital inputs/outputs and a serial RS485 interface are integrated. The GO firmware module is used to activate oscilloscope functions for voltage, and to set trigger signals for limit value events. A PT100 input is also provided.



Application

The device is used to measure residual currents in outgoing lines/sub-distribution systems. Therefore continuous monitoring in accordance with VDE 0105-100/A1 can be established, resulting in measuring the insulation resistance according to DGUV V3 being redundant.

Standard

INPUTS 3U, 5I	HARMONICS 128	SAMPLING 28,8 kHz	SUPPLY 230V	USB	ETH	NTP	INPUTS Pt100
INPUTS/OUTPUTS 4xDIGI	INPUTS RCM	WEBSERVER	BATTERY	FLASH 512MB	RS485	MODBUS	

Optional

STANDARDS class S IEC 61000-4-30	FIRMWARE GO	SUPRAHARMONICS 2 kHz...9 kHz
FIRMWARE RCS	STANDARDS EN 50160	

Supply voltage	Measurement voltage	Diff. current meas.	Functions				Communication				Type	Item number
			Digital inputs/ outputs	Memory size in MB	Clock	Pt100 input	RS485	Ethernet	Gateway Modbus master	USB		
65 - 275 V AC 75 - 350 V DC	5 - 1470 V LL	Number	4	512	•	•	•	•	•	•	UMD 707RCM	13.25.1104

Technical specifications - UMD 707RCM

UMD 707RCM						
Inputs and outputs	Digital inputs/outputs	4 digital inputs/outputs				
	Relay inputs/outputs	None				
	Analogue inputs/outputs	None				
	Differential current inputs	5 inputs				
	Temperature inputs	1 Pt100 input -50 - 170 °C				
Communication	Interfaces	RS485, Ethernet, Front-USB				
	Communication protocols	Modbus RTU, Modbus TCP/IP, SMTP, SNMP, DHCP, JSON				
Further functions	Alarms	integrated logic: Limit values for exceeding/falling below freely defined values				
	Internal temperature measurement	-40 - 85 °C				
Data logger	Storage capacity and allocation	512 MB flash freely partitionable into several archives				
	Measured value storage	Freely configurable measured values with different averaging intervals				
Electrical connection	Supply voltage	230 V variant: 85 - 250 V AC / 85 - 270 V DCc				
	Power input	10 VA / 5 W				
	Overvoltage category	CAT III / 300 V				
Accuracy classes	Voltage:	Cl. 0.1	Current:	Cl. 0.1	Frequency:	Cl. 0.02
	Harmonic oscillations:	Cl. 1				
Measuring inputs	Voltage	U L-N: 3 - 850 V AC				
		U L-L: 5 - 1470 V AC				
	Overload voltage	Permanent U L-N: 1300 V AC / peak overload for max. 1 sec. U L-N: 2210 V AC				
	Input impedance voltage	3.9 MOhm				
	Input load voltage	< 0.1 VA				
	Frequency	40 ... 70 Hz (DC-500 mode: 0 ... 500 Hz)				
	Transformers	5x RCM				
	Overload current	Permanent: 80 mA / peak overload for max. 1 sec: 120 mA				
	Input impedance current	100 Ohm				
	Input load current	< 0.2 VA				
	Sampling rate	28.8 kHz				
	Harmonics per order	1st ... 128. for current and voltage; Optional: Supraharmonics from 2 kHz ... 9 kHz				
Measurement procedure	IEC 61000-4-30 Cl. S					
Mechanical attributes	Operating temperature range	-25 - 60 °C at < 95 % relative humidity				
	Bearing temperature range	-30 - 80 °C at < 95 % relative humidity				
	Protection class front / total	IP 40 / IP 20				
	Dimensions WxHxD	108 x 90 x 61 mm				
	Weight	0.3 kg				
Internal real-time clock	Accuracy	+/- 0.2 s per day at 0 - 40 °C				
	Possible synchronisation	NTP/SNTP; External GPS receiver; External pulses; System frequency; PC time				
FW Module	PQ S: optional	GO: optional		RCS: optional		
	MM: optional	UDP: optional		IEC104: optional		
	SH: optional					

* depending on the variant